Antari®
FOG MACHINE
www.antari.com

HIGH PERFORMANCE HAZE ,
SURPRISINGLY SMART

Z-380 Series®

▪ Z-380 Real Panel

▪ Antari FLG Liquid

▪ Z-380 Effects

Features

1. 1500W huge capacity
2. Compact size yet powerful outputs
3. Both 3pin and 5pin in dual DMX connector
4. DMX offline auto power off function
5. User friendly LCD screen setup display
6. Equipped with hanger to add conveniences to your choice of hanging or lay flat
7. Big pipe design with smart auto cleaning function, no hassles for clogging by using Antari fog liquid
8. Adjusting fan volume in linen and ensure fog output smoothly
9. Easy connecting to 0-10V control

Specification

» Voltage : U.S. version : 120 Volt Europe version : 230 Volt
U.K. version : 240 Volt Japan version : 100 Volt
» Power Consumption : 1,500W
» Initial Heat-up Time : 1.5 mins
» Fluid Consumption Rate : 6 ml/min (100 % output)
» Tank Capacity : 1.2 Liters
» DMX Channel : Occupied 2 Channels
Channel 1 : Faze Output Volume
Channel 2 : Fan Volume
» Optional Remote : Z-3 Remote or W-2 Wireless Control
» Weight : 8.4 kg
» Dimensions(mm) : L 328 W 247.7 H 264.9
L 328 W 247.7 H 323.9(hanging bracket)
» Liquid Used : Antari FLG Liquid

Website - www.antari.com / Email - sales@antari.com

D08Z3800I

CE RoHS