

Microphone with zone selector for amplifier MPZ-6241.
For selecting up to 6 zones, paging and musical chimes in the amplifier.



M-62

CHARACTERISTICS	Microphone with 6-zone selector. Musical chimes. Ring and operating lights, zone and output level selection Zone selector and paging in amplifier mod. MPZ-6241.
MICROPHONE	Electret condenser with gooseneck
INPUTS	1 micro, 5-pin socket 1 link input, RJ-45
OUTPUTS	1 micro zone selector, RJ-45
CONNECTION	RJ-45 cable, distance greater than 500 m
POWER SUPPLY	24 V DC, 500 mA with adapter included, powered by amplifier or local power for distances greater than 50 m or more than 2 microphones
DIMENSIONS	Gooseneck microphone: 415 mm height Base: 175 x 54 x 147 mm depth
WEIGHT	1 kg
ACCESSORIES	RJ-45 connecting cable